



**Model #160WQ**

**Features :**

- \* Reverse voltage & overcurrent protection
- \* Stabilized power head & tail lights (w. energy backup by 0.22F SuperCap)

**Main characteristics :**

Dimensions (L x l x h) : 15 x 10 x 6 mm max (w. supercap)  
 Weight : 2.80 gr (w. power conn & supercap)  
 Power supply : min 8Vdc/ac - Max 25Vdc/ac (Davic compatible)  
 Power consumption : Max 68mA peak - 20mA continuous (@12.8Vdc)  
 Backup lighting : > 1 minute

**Model #160WQ RTM kit - P/N E225-0160-30-86**

**Parts list :**

- 1 ea. Basic PCB assy. ref# E225-0130-01-64
- 1 ea. Supercap 0.22F/5V5 ref# E225-0140-01-94
- 1 ea. Power male conn. ref# E225-0141-02-01
- 1 ea. Power female conn. ref# E225-0141-03-02
- 1 ea. Prewired quad front warm white PLCC leds ref# E225-01XX-XX-XX
- 1 ea. Prewired dual rear super red PLCC leds ref# E225-0143-03-08

**Rmk :** Leds & power male conn. already soldered

**#160WQ**  
 rev. 06/02/2011  
 Light kit  
  
**Zmachine**

<http://www.zmachine.be> - [phl@zmachine.be](mailto:phl@zmachine.be) - Zmachine Electric Motorsport